



## MP-4000 Non-Display Cloning

**Date:** November 22, 2020

Cloning refers to taking the programming information from one radio and copying it to one or more radios without the aid of a computer.

**Hardware Needed:** ACC-8050C Cloning Cable



	KEY COMBINATION	OPERATION
WIRED	<p>Source TX Radio: Key 4 (M button) + Power on LED will turn an amber color.</p> <p>Target RX Radio: Key 3 (P button) + Power on LED will be a green color.</p>	<p>1. Connect both radios with the cloning cable.</p> <p>2. Put both radios into Cloning Mode using their respective key combinations listed.</p> <p>3. When Cloning mode is ready, press Key1 (Emergency key) of the TX radio to send the data to the target RX radio. When complete, the LED of the TX Radio will turn green and the target radio LED will turn off. Disconnect both radios and test their operation. <b>If you want to clone additional radios</b>, leave the TX radio on (LED will be still be green) and connect a new target RX radio that is in cloning mode. Press Key 1 on the TX radio to copy the data.</p>

---

11535 West 83<sup>rd</sup> Terrace ▪ Lenexa, Kansas ▪ 66214

Telephone: 800-456-2071 ▪ Fax: 913-859-9550

Website: [www.maxonamerica.com](http://www.maxonamerica.com) ▪ Email: [maxon@maxonamerica.com](mailto:maxon@maxonamerica.com)