

Technical Service Bulletin

Date: April 20, 2006

Subject: SM2500 reset modification

Issue: EEPROM data loss

Corrective Action: Install two 47K (size 0603) pull-down resistors between pins 5&6 and 1&2 of CON403. Next install the IC supervisor, ADM809LARTZ as shown below.

Parts list: Part number RHM47KGCT-ND. 47K resistor, 0603
Part number ADM809LARTZ. IC supervisor

